A-ANTENNAS

791-862MHz (B20), 1710-1880MHz (B3)
B3 <6.0 dBi
B20 <6.2 dBi
<3:1
B3 >-2.5dB (>56%)
B20 >-3dB (>50%)
50Ω
Yes
Omni-directional
Linear
>10W
AA100 Low loss
Grey
1.5m
MCX male RA (90°)
Center screw
IP66
Yes
-40°C to +85°C
RH 95% non condensing
>100km/h
>10years
>15years
L 160mm, W 48mm, H 45mm
125g
Grey
Grey

[©] A-Antennas * The total efficiency and VSWR is depending on materials in the near field of the antenna and size/shape of GND. The values in the specification are typical values

itennas





Mounting instructions

Antennas

Mount the antenna with suitable screws with flat underside. Screws thicker than the mounting hole might damage the antenna.

Note that the cable is sensible for squeezing and sharp bends. Minimum

The antenna can be mounted directly on metal (like a metal cabinet), wooden and plastic surfaces and in free space on a pole.

© A-Antennas

^{**} Other cable lengths and connector available on demand