A-ANTENNAS

QUAD NB-IOT SWE

135

Frequency		791-862MHz (B20)
		1710-1880MHz (B3)
Gain*	B3	0dBd (≈2dBi)
	B20	0dBd (≈2dBi)
VSWR*		<2:1
Impedance		50Ω
Efficiency	B3	Better than -2dB
	B20	Better than -3dB
Cable**		Low loss
Cable length**		1.5m
Cable loss		<0.85dB/m @ 2GHz
Connector**		SMA/SMB/FAKRA/FME
Mounting method		Screw mount
		optional: Adhesive, Magnet
Temperature range		-40°C to +85°C
Maximum humidity		RH 95% non condensing
Wind resistance		>150km/h
IP Class		IP66
UV protection		>10 years
Product lifetime		>20years
ROHS/WEEE/CE		Yes
Dimensions		158x47mm
Weight		120g
Color		Grey

* The total efficiency and VSWR is depending on materials in the near field of the antenna and size/shape of GND. The values in the specification are typical values

** Other cable lengths and connector available on demand



Mounting instructions

C A-Antennas

Antennas

R

Mount the antenna with suitable screws with flat underside. Screws thicker than the mounting hole might damage the antenna.

Note that the cable is sensible for squeezing and sharp bends. Minimum bending radius R10.

The antenna can be mounted directly on metal (like a metal cabinet), wooden and plastic surfaces and in free space on a pole.



C A-Antennas

Phone: +46 (8) 540 20 000 Mail: info@a-antennas.se

tennas

C A-Antennas